



POWERING YOUR *life.*

Model 201299

UPC 817198026794

Warranty 3 Years

6875
STARTING WATTS

5500
RUNNING WATTS

RUN TIME 10 hrs. NOISE LEVEL 74 dBA

INTELLI GAUGE
4-MODE digital meter

COVERED OUTLETS
PROTECT outlets from the elements

VOLT GUARD
Protects against **POWER SURGES**

COLD START
Easy starts in **COLD WEATHER**

Receptacles



23 AMP
120/240V, L14-30R



20 AMP GFCI
120V, 5-20R



20 AMP GFCI
120V, 5-20R

Specifications

| | |
|---------------------------|--------------|
| START TYPE | Recoil |
| VOLTAGE (V) AC | 120/240 |
| VOLTMETER | Intelligauge |
| ENGINE SIZE (cc) | 389 |
| FUEL TYPE | Gasoline |
| GASOLINE CAPACITY (gal.) | 7.7 |
| OIL TYPE | 10W-30 |
| OIL CAPACITY (fl. oz./mL) | 37.2/1100 |
| LOW OIL SHUT-OFF | Yes |
| EMISSIONS | EPA III |

*Specifications, descriptions and illustrations are subject to change without notice.



**CARBON MONOXIDE
AUTO-SHUTOFF**



Convenient and versatile power is yours with the Champion 5500-watt portable generator, featuring CO Shield® carbon monoxide auto shutoff system. Rely on the Champion 389cc engine and enjoy up to 10 hours of run time at 50% load with a noise level of 74 dBA.

Inside the box

GENERATOR
WHEEL KIT
ENGINE OIL

OPERATOR'S MANUAL
OIL FUNNEL

What You Need

GASOLINE
PLIERS

WRENCH/SOCKET SET

PACKAGE (gross)
Weight: 170.9 lb.
Size: 29.5 x 22.6 x 24 in.

PRODUCT (net)
Weight: 155.5 lb.
Size: 28.2 x 27.2 x 25 in.

CHAMPION POWER EQUIPMENT, INC.
www.championpowerequipment.com